SECTION AB46.423C Issue 1, December 1962 A.T.& T. Co. Standard

ELECTRON TUBE DATA SHEET WESTERN ELECTRIC 423C ELECTRON TUBE



DESCRIPTION

The 423C is a two-electrode inert-gas filled cold cathode tube designed primarily for use as a voltage reference tube. This tube has characteristics which are exceptionally stable with life and with variations in ambient temperature.

go treo edur. (zemivier la lisari un rest estrus; per estrus; per estrus de la sella variata el culta de estrus estruses de la companya del companya de la companya de la companya del companya de la companya del companya de la companya de la companya de la companya de la companya del companya de la companya del companya del companya del companya de la companya del companya del

Cathode Current	mperes
Anode Voltage Drop	volts
Regulation at 4 to 6 milliamperes d-c (Note 5-page 3) 0.75	volt

File: Cold Cathode Section

RATINGS, Absolute System (Note 1)				
Cathode Current, Forward Maximum	• • • •		4 0. 0	milliamperes milliamperes milliampere centigrade
ELECTRICAL DATA, Throughout Life				
		Min. Bog	ey <u>Max.</u>	
Anode Breakdown Voltage · · · · · · ·		• - 13	5 160	volts
Anode Voltage $Drop(E_{td})$ at 6 Milliamperes(1	D-C)Note 2	• 99 10	0 103	volts
Regulation (4 to 6 Milliamperes, D-C) (Note	5) • • •	· - 0.	3 0.75	volt
Temperature Sensitivity of Anode Voltage 1	Drop			
Anode Current, 4 Milliamperes (D-C) · ·		·0.0	_	volt/c
Anode Current, 8 Milliamperes (D-C) · ·		•0.0		volt/c
Fluctuation (Note 3) $\cdot \cdot \cdot$		• - 0.0		volt
Average Ionization Time (Note 4) \cdot · · · ·		• - 4.	0 6.0	milliseconds
MECHANICAL DATA				
Mounting Position			• •	Any
Net Weight, Approximate			• •	0.3 ounce
Bulb				т 6¼
Base			. Small	Button 9 pin
Dimensions and connections shown in outlin	ne drawing	on page 4.		-
LIFE DATA				
Regulation (4 to 6 mAdc) after 1000 hours	at 5 mAdc	(Note 5).		See Figure 1
Drift in Anode Voltage Drop (Etd) in 1000	hours at	5 mAdc · ·		See Figure 2
HANDI INC				

HANDLING


This tube contains a small amount of krypton-85 gas which is a by-product radioactive material. The amount of krypton-85 is less than five microcuries, which is too small an amount to require any special care in use.

Atomic Energy Commission regulations require that the individual tube carton for tubes containing by-product radioactive material be appropriately marked. The marking includes the statement that tube disposal should be in approved manner.

Approved instructions for disposal of tubes containing krypton-85 are as follows;

Tubes to be disposed of should be broken or crushed in a well ventilated place releasing any resulting vapors to the outside atmosphere. The residual broken or crushed tubes should be disposed of in a normal public trash disposal system. Tubes should be disposed of at a rate of not more than 100 each week from any one location. Avoid breathing vapors from broken tubes.

Note 1: In the "Absolute System" the maximum ratings specified are limiting values above which the serviceability of the device may be impaired from the viewpoint of life and satisfactory performance. Maximum ratings, as such, do not constitute a set of operating conditions and all values may not, therefore, be attained simultaneously.



DRIFT OF ANODE VOLTAGE OVER 1000 HOURS 5 mAdc LIFE 2.0 5 mAdc OPERATION (DRIFT) FIRST SAMPLE DATA LIFE LOTS II IV 60 TO 12 II 62 135 TUBES STUDIED REPRESENTING 28000 △ Etd IN Vdc TUBES TO STOCK 0.5 0.3 DURING 0.1 50 70 80 90 95 99.8 98 99 PERCENT OF UNITS BELOW ORDINATE VALUE


Note 2: These values are for new tubes. Anode voltage drop will stabilize within 3 minutes after starting.

FIG. 2

Note 3: The anode voltage drop variation during a short period of time (one to ten minutes), with the tube operating at one value of current and temperature within its ratings, will not exceed the above stated maximum value.

Note 4: With 15 volts overvoltage (15 volts above Anode Breakdown Voltage) with tube in total darkness. Average of 10 measurements taken at 1 second intervals.

Note 5: Regulation is defined to be Anode Voltage Drop (E_{td}) at 6 mAdc minus Anode Voltage Drop (E_{td}) at 4 mAdc.



į

NOTE: PINS MARKED IC (INTERNAL CONNECTION) SHOULD NOT BE CONNECTED TO ANY PORTION OF AN EXTERNAL CIRCUIT. FAILURE TO OBSERVE THIS PRECAUTION MAY RESULT IN IMPROPER OPERATION OF THE TUBE.

A development of Bell Telephone Laboratories, the research laboratories of the American Telephone and Telegraph Company and the Western Electric Company.